

COMMON MODE FEEDBACK AMPLIFIER

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to a common mode feedback
5 amplifier circuit and method, and more particularly to a common
mode feedback amplifier circuit for reduction of signal distortion.

2. Description of the Prior Art

For the requirements of the typical common mode feedback
(CMFB) amplifiers, the direct current (DC) voltage level of the
10 output signal is required to be maintained at the same level as the
reference voltage, and is to be prevented from being influenced by
the DC voltage level of the differential input signals.

Normally, a detecting circuit is included in the CMFB
amplifier, in order to detect and correct the DC voltage level of the
15 differential output signals of the CMFB amplifier. When the DC
voltage level of the two output signals is different from the
reference voltage, the detecting circuit will suitably correct the DC
voltage level of the output signals of the CMFB amplifier, until the
DC voltage level of the output signals is adjusted to the reference
20 voltage.

However, every detecting circuit of the CMFB amplifier may
have its own working limit. Accordingly, once the DC voltage level
of the output signals is far deviated from the reference voltage, the
detecting circuit may not be able to suitably correct or adjust the DC
25 voltage level of the output signals of the CMFB differential
amplifier back to the reference voltage.

When the CMFB amplifiers are working or operating for large

signals, deviation of the DC voltage of the differential outputs becomes worse. As such the DC voltage may drift to a higher value or a lower value. In either case the output signals may be distorted accordingly, such that the operating range of the output signals will be limited, and such that the operating range of the input signals will also be limited.

In order to prevent the distortion of the output voltage signals, U.S. Patent No. 5,729,178 to Park et al. provides a fully differential cascode operational amplifier (OP AMP) having an adaptive biasing circuit to eliminate the effect of slew rate. The amplifier has two outputs V1 and V2 compared with a reference voltage VCMREF. However, when $V1=V2$ and when V1 and V2 are much greater than the reference voltage, the signals may not be suitably adjusted back to the reference voltage.

The working range may have been improved by Park et al., however, the DC voltage level of the output signals may still be greatly deviated from the reference voltage under certain circumstances.

U.S. Patent No. 6,448,848 to Altmann discloses a differential transconductor-capacitor (gm-C) circuit employing two transistors to calibrate or adjust the output signals. The control signals are coming from the voltages of a detecting circuit. However, in the detecting circuit, the common mode reference voltage is not compared directly with input signals, instead it is compared with intermediate signals out and outB, such that output signals may not be accurately controlled.

When the two output signals out and outB may not be

completely symmetric to each other, due to the manufacturing procedures of the semiconductor process, the voltage difference may not be suitably improved by the detecting circuit. The detecting circuit may only be used to improve the average voltage of the two
5 output signals, such that the two output signals out and outB may have different DC voltage levels, and such that signal distortions may occur for large signals.

The present invention is to mitigate and/or obviate the afore-described disadvantages of the conventional common mode
10 feedback amplifier.

SUMMARY OF THE INVENTION

The primary objective of the present invention is to provide a common mode feedback amplifier including an improving circuit or structure to maintain the DC voltage of the output signals at the
15 reference level, and to prevent the output signals from being distorted.

In accordance with one aspect of the invention, there is provided a method for improving a common mode feedback amplifier, the method comprising mixing signals of the common
20 mode feedback amplifier, to increase working range of the common mode feedback amplifier, and to prevent output signals of the common mode feedback amplifier from being seriously distorted due to operating limit of the common mode feedback amplifier.

In accordance with another aspect of the invention, there is
25 provided a common mode feedback amplifier comprising a common mode feedback amplifier unit including two input signals as differential input signals; i.e., the input signals are equal but reverse

to each other, the two output signals are also differential output signals. The common mode feedback amplifier may not suitably adjust the DC voltage of the two differential output signals, in which the common mode feedback amplifier includes a symmetric
5 circuit, such that the DC voltage of the two differential output signals may deviate toward the same direction, such that the two differential output signals may be distorted when large output signals are generated or output.

In order to improve the problem, the common mode feedback
10 amplifier in accordance with the present invention is to provide two sets of symmetric gain amplifiers coupled to the two output terminals for the two differential output signals from the common mode feedback amplifier, in order to improve the signal distortion problem when the DC voltage of the two differential output signals
15 from the common mode feedback amplifier is deviated toward the same direction to cause large output signals to be distorted.

When the DC voltage of the differential output signals of the CMFB amplifier is deviated to one direction and the differential output signals are distorted and are input to the gain amplifiers,
20 these two differential signals are coupled to the positive and the negative input terminals of a gain amplifier, such that these two deviated and distorted differential signals will be combined or mixed in phase by the amplifiers, and such that the distorted portions of the signals will be complementary with each other, in
25 order to decrease the distortion thereof.

The other gain amplifier is identical to the previous gain amplifier, but has two differential input signals arranged in opposite

order, such that the output signal of the other gain amplifier will be differential relative to the output signal of the previous gain amplifier, such that the two gain amplifiers may provide improved differential output signals that have low distortion.

5 Further objectives and advantages of the present invention will become apparent from a careful reading of the detailed description provided hereinbelow, with appropriate reference to the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

10 FIG. 1 is a plan schematic view illustrating a circuit of a common mode feedback amplifier in accordance with the present invention;

FIG. 2 is a plan schematic view illustrating the waveforms of the common mode feedback amplifier having no gain amplifiers
15 included therein; and

FIG. 3 is a plan schematic view similar to FIG. 2, illustrating the waveforms of the common mode feedback amplifier having the gain amplifiers included therein.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

20 Referring to the drawings, and initially to FIG. 1, a common mode feedback amplifier in accordance with the present invention comprises a common mode feedback amplifier unit 1 for amplifying and detecting the difference between DC voltage of the output signals and a reference voltage, and calibrating or adjusting the DC
25 voltage to the reference voltage, a differential adjusting unit 2 of symmetric gain amplifiers for cancellation of distorted part of the differential signals.

The common mode feedback amplifier unit 1 includes a common mode feedback circuit (CMFB) 11, and a differential amplifier 12 having two differential input signals V_{i+} and V_{i-} , and having two output terminals 13, 14 coupled to the CMFB 11, for transmitting output signals V_{a+} and V_{a-} to the CMFB 11. The CMFB 11 includes a reference signal V_{ref} input thereto, and includes a feedback or control signal V_{cm} output to the differential amplifier 12, in order to generate a feedback signal to control the DC voltage of the output signals V_{a+} and V_{a-} of the differential amplifier 12.

The differential adjusting unit 2 includes two sets of gain amplifiers 21, 22 each having an amplifier 23, 24 respectively. The amplifiers 23, 24 each includes a negative input terminal 25 coupled to the output terminals 13, 14 of the differential amplifier 12 via a resistor 27 respectively, and a positive input terminal 26 coupled to the other output terminals 14, 13 of the differential amplifier 12 respectively.

The gain amplifiers 21, 22 of the differential adjusting unit 2 each may further include a feedback resistor R_f 28 coupled between the negative input terminal 25 and an output terminal 29 of the amplifiers 23, 24 respectively for gain control. The differential adjusting unit 2 may receive and mix or blend the output signals V_{a+} and V_{a-} of the differential amplifier 12, and may complement the distorted part of the signals with each other and may generate output signals V_{b+} and V_{b-} , to prevent the output signals V_{b+} and V_{b-} from being distorted.

In operation, the CMFB 11 is coupled to the output terminals

13, 14 of the differential amplifier 12, to receive the output signals V_{a+} and V_{a-} from the differential amplifier 12, and to check or detect the difference between the DC voltage of the output signals V_{a+} and V_{a-} of the differential amplifier 12 and the reference signal V_{ref} . The CMFB 11 may then correct or adjust the feedback or control signal V_{cm} , to actuate or to correct or to adjust the DC voltage at the output terminals 13, 14 of the differential amplifier 12, until the DC voltage of the output signals V_{a+} and V_{a-} of the differential amplifier 12 equals to the reference signal V_{ref} of the CMFB 11.

However, the CMFB 11 has a working limit, and the DC voltage of the output signals V_{a+} and V_{a-} of the common mode feedback amplifier unit 1 may normally be deflected from the reference signal V_{ref} to either higher or lower voltage. The output signals V_{a+} and V_{a-} may thus be distorted. If the DC voltage of the differential signals has higher voltage then the differential signals are squeezed when the signals are high and extended when the signals are low because the space between the DC voltage and power source V_{cc} is smaller and the space between the DC voltage and the ground is larger. On the other hand if the DC voltage of the differential signals has lower voltage then the differential signals are squeezed when the signals are lower and extended when the signals are high for the same reason as described above. The deflection or distortion may be greatly increased particularly when the input signals are large. The waveforms of the output signals V_{a+} and V_{a-} of the common mode feedback amplifier unit 1 are shown in FIG. 2.

The gain amplifiers 21, 22 of the differential adjusting unit 2 are coupled to the output terminals 13, 14 of the differential amplifier 12, to amplify and combine the output signals V_{a+} and V_{a-} of the common mode feedback amplifier unit 1. The gain amplifiers 21, 22 of the differential adjusting unit 2 may prevent the output signals V_{b+} and V_{b-} from being distorted.

The relationship between the output signals V_{b+} and V_{b-} and V_{a+} and V_{a-} is as follows:

$$V_{b+} = V_{a+} + (V_{a+} - V_{a-}) \times (R_f/R), \text{ in which}$$

$$V_{a+} = -V_{a-}, \text{ such that } V_{b+} = (R+2R_f)/R \times V_{a+};$$

Similarly, $V_{b-} = -(R+2R_f)/R \times V_{a+};$

The differential gain A_{vdiff} of the gain amplifiers 21, 22 may thus become:

$$A_{vdiff} = (V_{b+} - V_{b-}) / (V_{a+} - V_{a-})$$

$$= (R+2R_f)/R; \quad \text{or} \quad 1 + 2R_f/R.$$

Under the common mode: $V_{b-} = V_{a-}$; and $V_{b+} = V_{a+}$; and thus $V_{b+} = V_{b-} = V_{a+} = V_{a-}$, such that the common gain A_{vcom} of the gain amplifiers 21, 22 may thus become:

$$A_{vcom} = (V_{b+} - V_{b-}) / (V_{a+} - V_{a-}) = 1.$$

As a result,

$$A_{vdiff}/A_{vcom} = 1 + 2R_f/R.$$

Accordingly, the common gain A_{vcom} of the gain amplifiers 21, 22 equals to one (1), and the differential gain A_{vdiff} of the gain amplifiers 21, 22 may be greater than one (1). This indicates that the DC voltage of the output signals V_{b+} and V_{b-} of the gain amplifier devices 21, 22 of the differential adjusting unit 2 may thus be maintained at the same level while the distortion of the output

signals V_{b+} and V_{b-} is improved by a factor of $1 + 2R_f/R$.

The gain amplifiers 21, 22 of the differential adjusting unit 2 may thus be used as a means or device to combine the output signals V_{a+} and V_{a-} of the common mode feedback amplifier unit 1, and to
5 output and maintain the DC voltage of output signals V_{b+} and V_{b-} of the gain amplifier devices 21, 22 at the reference signal V_{ref} , and may reduce the distortion level of the output signals V_{b+} and V_{b-} due to the nature of symmetric distortion of the differential signals from CMFB amplifiers and the voltage gain of the differential
10 adjusting amplifiers as described before.

Accordingly, the common mode feedback circuit in accordance with the present invention includes an improving circuit or structure to maintain the output signals at the reference signal, and to prevent the output signals from being distorted.

15 Although this invention has been described with a certain degree of particularity, it is to be understood that the present disclosure has been made by way of example only and that numerous changes in the detailed construction and the combination and arrangement of parts may be resorted to without departing from
20 the spirit and scope of the invention as hereinafter claimed.